

# PowerView<sup>™</sup> Analog Gages - PVA Series



#### **Features**

- For modern electronic engines and equipment using SAE J1939 Controller Area Network
- Display SAE J1939 parameters broadcast by the PowerView system
- Cutting edge, stepper motor technology and robust functionality combined
- Microprocessor driven for high accuracy
- Simple installation and wiring design

The **PowerView Analog Gages (PVA)** are a series of intelligent gages designed to display easy-to-read information transmitted by the PowerView. The PVA gages communicate with the PowerView via a single RS485 twisted pair MODBUS® RTU serial link. The gages can be daisy-chained using quick-connect harnesses with watertight connectors.

The major feature of the PVA gages is their balance between design and functionality. These modern gages offer a selection of lens and bezel styles and colors.

The PVA gages also include features such as a smooth stepper motor operation for the 270°sweep pointer, an environmentally sealed case with two Deutsch DT style connectors molded into the casing, and green LED back lighting. They are available for standard 2-1/6" (52mm) and 3-3/8" (86mm) diameter hole sizes. In addition their plastic cases incorporate a "D" shape allowing panel cutouts that eliminate gage rotation during installation.

The **PowerView Audible Alarm (PVAA)** alerts operators to fault conditions via piezoelectric alarm and relay contacts. It also has a temporary silencer button that silences the audible tone for 2 minutes on warnings and 30 seconds on shutdown conditions.

All PowerView gages can be powered by 12 or 24 VDC systems.

### PVA20 Series Models: 2 inch size gages:

PVA20 -A = Engine Oil Pressure

PVA20 -B = Coolant Temperature

PVA20 -C = Voltmeter

PVA20 -D = Percent Load at Current RPM

PVA20 -E = Transmission Oil Pressure

PVA20 -F = Transmission Oil Temperature

PVA20 -G = Engine Oil Temperature

PVA20 -H = Hydraulic Oil Temperature

PVA20 -J = Percent Fuel Level

PVA20 -K = Boost Pressure

PVA20 -L = Exhaust Gas Temperature

PVA20 -M = Intake Manifold Temperature

PVA20 -N = Auxiliary Temperature

PVA20 -P = Auxiliary Pressure

PVA20 -T = Tachometer

PVAA20 = Audible alarm

### PVA35 Series Models: 3-1/2 inch size gages:

PVA35 -T = Tachometer

PVA35 -S = Speedometer

#### **Specifications**

Power Supply Input Voltage: 12/24V (8-32VDC min. & max. voltage)

Power Supply Operating Current: (@ 14VDC) =

PVA20, PVA35: 28 mA minimum; 52 mA maximum PVAA20: 19 mA minimum; 46 mA maximum

Backlight Maximum Current (not applicable to PVAA20): 24mA

Input: RS485 MODBUS© RTU data

Output: Analog readout

Sound Output Level (PVAA20): 90 dB @ 30 cm

Relay Rated Load (PVAA20): 0.5A, 125 VAC; 1 A, 24 VDC Relay Maximum Switching Capacity (PVAA20): 62.5 VA, 30W

Exterrnal Audible Alarm Output (PVAA20): 28 VDC, 30 mA maximum (current sink)

Temporary Silence Button (PVAA20): Charge transfer technology.

Operating Temperature: -40° to 185°F (-40° to 85°C) Storage Temperature: -76° to 185°F (-60° to 85°C)

Dial: White numerals over black background


Indicating Pointer: Stepper motor operation with 270° sweep.

Gage Accuracy: PVA20: Better than ± 1.0% scale.

PVA35: Better than ± 2% of scale Environmentally Sealed Enclosure: Sealing: IP68, ±5 psi (±34.4 kPA)

Case and Clamp Material: Polyester (PBT)

Lens Material: Polycarbonate
Bezel Material: Polyester (PBT)
Maximum Panel Thickness: 3/8 in. (9.6mm)
Connectors: 6-Pin Deutsch DT06 Series




**Warranty** - A limited warranty on materials and workmanship is given with this FW Murphy product. A copy of the warranty may be viewed or printed by going to http://www.fwmurphy.com/warranty

## Contemporary Domed Bezel and Lens Style




### PVA20 Series - Typical Gage Dimensions



#### EB Domed Bezel and Lens Type



### PVA35 Series - Typical Gage Dimensions



#### EB Domed Bezel and Lens Type



### PVAA20 Model - Audible Alarm Typical Dimensions

